

DIAGNOSTIC TROUBLE CODE CHART

If a DTC is displayed during the DTC check, check the circuit listed in the table below and proceed to the page given.

DTC No. (See Page)	Detection Item	Trouble Area	Multi Warning Light*	Memory
P0500/61 (DI-24)	Vehicle Speed Sensor Malfunction (Vehicle Speed Sensor)	<ul style="list-style-type: none"> • Open or short in vehicle speed sensor circuit • Vehicle speed sensor • Combination meter • Engine and ECT ECU • Automatic transmission (clutch, brake or gear etc.) 	●	○
P0710/38 (DI-27)	Transmission Fluid Temperature Sensor Circuit Malfunction (ATF Temperature Sensor)	<ul style="list-style-type: none"> • Open or short in ATF temperature sensor circuit • ATF temperature sensor • Engine and ECT ECU 	●	○
P0715/67 (DI-29)	Input/Turbine Speed Sensor Malfunction (O/D Direct Clutch Speed Sensor)	<ul style="list-style-type: none"> • Open or short in O/D direct clutch speed sensor circuit • O/D direct clutch speed sensor • Engine and ECT ECU 	●	○
P0753/62 (DI-32)	Shift Solenoid A Electrical Malfunction (Shift Solenoid Valve No. 1)	<ul style="list-style-type: none"> • Open or short in shift solenoid valve No. 1 circuit • Shift solenoid valve No. 1 • Engine and ECT ECU 	●	○
P0758/63 (DI-32)	Shift Solenoid B Electrical Malfunction (Shift Solenoid Valve No. 2)	<ul style="list-style-type: none"> • Open or short in shift solenoid valve No. 2 circuit • Shift solenoid valve No. 2 • Engine and ECT ECU 	●	○
P1755/68 (DI-36)	Linear Solenoid for Lock-up Control Circuit Malfunction (Shift Solenoid Valve SLU)	<ul style="list-style-type: none"> • Open or short in shift solenoid valve SLU circuit • Shift solenoid valve SLU • Engine and ECT ECU 	-	○
P1760/77 (DI-39)	Linear Solenoid for Line Pressure Control Circuit Malfunction (Shift Solenoid Valve SLT)	<ul style="list-style-type: none"> • Open or short in shift solenoid valve SLT circuit • Shift solenoid valve SLT • Engine and ECT ECU 	-	○
P1765/46 (DI-43)	Linear Solenoid for Accumulator Pressure Control Circuit Malfunction (Shift Solenoid Valve SLN)	<ul style="list-style-type: none"> • Open or short in shift solenoid valve SLN circuit • Shift solenoid valve SLN • Engine and ECT ECU 	-	○

* : ●...Multi Warning Light Lights Up